

Overview

The SceneStation Programmer's IR Remote is a handheld remote control that is used to program and operate a SceneStation.

The 33-button remote has keys for recalling a scene, adjusting the grandmaster, lock, setting station options, scene programming and more.

The remote can be programmed to transmit 6 different security codes, allowing an installation with multiple SceneStations to be segmented into different IR control groups.

Either a Programmer's Remote or Wireless USB Interface is required to program a SceneStation.



Features

- Used for programming and/or operation
- 33 Buttons
- Transmit LED
- 6 different security codes
- 2 "AAA" batteries included

Specifications

Feature	Detail	Description
Buttons	Quantity	33
Power	Batteries	2x AAA
Physical	Width	2.0" (50 mm)
	Length	6.6" (167 mm)
	Height	0.9" (24 mm)
	Weight	3.2 oz. (91 g)
Environmental	Operating Temperature	-40° to 158° F (-40° to 70° C)
	Storage Temperature	-40° to 176° F (-40° to 80° C)
	Humidity	5 to 95%, non-condensing
	Altitude	10,000 feet maximum

Ordering

SS-IR33 Programmer's IR Remote

Setting Security Code

Hold down both **POWER** and **ENTER** for 3 seconds. Status LED will turn on. Release the buttons.

Press "1".

Press one of the following:

- Scene** = Code 1
- Indicator** = Code 2
- Repeat** = Code 3
- Fade** = Code 4
- Follow** = Code 5
- Loop** = Code 6

Press **ENTER**.

The Status LED will blink twice to confirm that the code has been set.

Distributor:



Phone: 407-857-8770
 Fax: 407-857-8771
 Email: sales@techni-lux.com
 www.techni-lux.com